

# Professional Mono Laser Printer

Super-fast wireless printing  
and large paper input tray

HL-L6210DW



PRINT

2.4GHz

WIRELESS

[www.brother.co.za](http://www.brother.co.za)



## Professional Mono Laser Printer

Designed to deliver professional performance with flexible connectivity options and super-fast, quality printing you can depend on.

The high-yield inbox toner means you can print for longer whilst considerably reducing your print spend. This, together with the robust build quality and flexible paper handling options, makes the HL-L6210DW the ideal print partner for your business.

### HL-L6210DW



### Key features

- Print up to 50 pages per minute
- 2-Sided print, up to 24 sides per minute
- Gigabit ethernet and 2.4GHz WiFi
- 1GB Internal memory
- 520 Sheet paper input tray expandable up to 1,560 <sup>11</sup>
- Comes with 6,000 page yield toner, 25,000 maximum yield available <sup>7</sup>
- Compatible with Brother and 3rd Party solutions<sup>19</sup>



### Secure by Design

To keep pace with the ever-evolving legislation on privacy and data security, our devices offer the latest industry-standard security features to securely protect your data.

All our products are secure as standard. With businesses shifting towards Zero Trust environments, we know that security is your highest priority. Our security experts continuously research new enhancements to products, solutions and services to proactively ensure all our products are 'secure by design'.

The HL-L6210DW provides a range of robust features. It uses triple-layer security at a device, network and document level which is verified through external security certification. This offers added peace of mind and guarantees that the integrity of your data is maintained at every step.


The HL-L6210DW comes with a flexible suite of security features and solutions that can be tailored to your business, enabling you to easily audit, control and manage your fleet of devices securely.



Your device protects your business by reducing its attack surface through:

**Restricting privileges at a device level** - with Secure Function Lock and Setting Lock, only authorised users are permitted access to specific functions.

**Maintaining device integrity** - with runtime intrusion detection, Secure Boot, digitally signed firmware and end-to-end encrypted connections, devices are always performing at their optimum level of security.



Your network is protected with flexible industry standard features and management tools including:

**Intrusion protection** - with protocol management, interface restrictions and IPV4 filtering, you have the flexibility to adapt device settings to your business.

**Secure connection** - securely connect to enterprise level wired and wireless networks through industry standard IEEE 802.1X.

**Secure encrypted communication** - by using flexible industry standards such as TLS, SSH, IPSEC, HTTPS and SNMP3, your business can tailor the device to its network.

**Easily manage and configure your security profile** - using Device Master Settings, BRAdmin Pro 4 and Mass Deployment Tool, your business can apply settings to entire fleets of devices.

**Audit your devices** - using SIEM integration through Syslog, you can gather real time usage information on your devices.





As working conditions change, security is more critical than ever. That's why each single function printer and all-in-one comes equipped with a range of features that deliver enterprise level security.

To safeguard data against loss or theft, Transport Layer Security (TLS), Secure Socket Layer (SSL), IPsec and Scan to SSH Server (SFTP) are supported so that your most confidential files transfer using up to 256-bit encryption during transmission over the network. Using automatic intrusion detection, devices recognise abnormal activity and take preventative measures in order to ensure the printer remains secure.

Plus, identity management and access control help to reduce risk with selective user restriction, only allowing authorised employees or groups to get instant access to specific settings and functions they need.



Your documents are protected through encryption, storage protection and secure print solutions including:

**Encrypted document transfer** - when you send your print data from your computer to the device, IPPS/HTTPS encryption ensures your data is secure and unreadable.

**Non-persistent internal memory** - all print job data is automatically wiped during a reboot and data is purged, ensuring no information is left on the device.

**Secure print release** - using a Brother secure print solution, documents are only released when you are ready to print and collect them.

**Optional 3rd party integration\*** - through Brother Solutions Interface (BSI), our devices can be fully integrated with trusted 3rd party partners such as Kofax, YSoft, and more. These add an extra layer of security to your business.

*\*Optional third party utilities compatible with the HL-L6210DN will require additional purchase.*





## Solutions Enabled

### Unlock new possibilities with our range of Brother Pro Upgrades\*

Automate workflows and improve business processes and security with print management solutions.

We offer a suite of document management, security and workflow solutions which can be added to the HL-L6210DN to provide additional professional features to further improve your business processes.



## Printer Management

### Remote Panel\*

#### Remote printer support

Remote Panel operates in real-time, offering a complete interactive interface to your printer. Your IT provider can access the full functionality of your printer, to quickly diagnose and resolve any issues and enable settings to be changed as if they were physically standing at the printer.

### Request Help\*

#### Diagnostic reports for IT administrators

Request Help is a Brother service that enables your IT administrator or service provider to easily troubleshoot errors that may occur. You simply press the 'Request Help' icon on the control panel and a full diagnostic report is created and automatically emailed to your IT administrator.

### Order Supplies\*

#### Order supplies from your printer

Effortlessly order your toner cartridge supplies directly from your printer, with the Order Supplies service. In one touch, your selected supplier will be notified when you require replacement supplies and arrange delivery, ensuring you never run out of toner when you need it.

*\*Brother Pro Upgrades are optional and will require additional purchase.*







## Security Solutions

### Secure Print Plus\*

Print secure documents from a specific printer

Secure Print+ enables you to print your confidential business documents securely. Your sensitive documents are only printed when you are ready to collect them from the printer. Only authorised staff can collect their documents and users are easily added or removed.

### Advance Secure Print\*

Print your document from any printer connected to your network

Pull printing is a unique way of printing wherever you are in the office. Advance Secure Print enables you to print your document from any printer connected to your network using a PIN or with a tap of an authorised NFC card. Brother Advance Secure Print works with compatible devices activated with this feature.



## Workflow Solutions

### Barcode Print Plus\*

Printing barcode fonts with ease

Brother's Barcode Print+ enables you to easily print barcodes from your Brother printer. You simply supply your printer with the information for the barcode, the barcode is then printed exactly as it should appear. The quality of the barcodes reflects Brother's exceptional printing standards. So, The printed 2D and 3D barcode is easily read by a variety of barcode readers and scanners.

*\*Brother Pro Upgrades are optional and will require additional purchase.*



## General

### Technology

Electrophotographic Laser

### Memory

1GB

### Control panel

1 Line LCD with Keys

### Local Interface

Hi-Speed USB 2.0

### Wired Network

Gigabit Ethernet

### Wireless Network

2.4GHz Support

### Carton Contents

Printer, Inbox Toners, Drum, Power Supply Cord, Quick Set-Up Guide

## Print

### Print Speed (A4)

1-Sided: 50ppm Mono  
2-Sided: 24 sides  
per minute Mono

### FPOT (First Print Out Time)

Up to 6.7 Seconds Mono

### Quiet Mode

A mode to reduce the printing noise

### Resolution

Up to 1200 x 1200dpi

### Print Languages

PCL6, BR-Script3, IBM  
Proprinter XL, Epson FX-850,  
PDF Version 1.7

### Embedded Fonts (PCL)

73 scalable fonts,  
12 bitmap fonts

### Embedded Barcodes (PCL)

16 bar codes\*  
\*Code39, Interleaved 2 of 5,  
FIM (US-PostNet), Post Net  
(US-PostNet) EAN-8, EAN-13,  
UPC-A, UPC-E, Codabar, ISBN  
(EAN), ISBN (UPC-E), Code128  
(set A, set B, set C), EAN128  
(set A, set B, set C), Code93,  
GS1Databar, MSI

### Embedded Fonts (Postscript)

66 scalable fonts

## Printer Functions

### N-up Printing

Reduce up to 25 pages into  
a single page

### Poster Printing

Enlarge a single page into a  
poster using 2x2, 3x3, 4x4  
or 5x5 pages

### Toner Save Mode

Use the Toner Save Mode to  
reduce toner consumption  
without affecting print speed

### Watermark Printing

Watermark your documents  
with predefined text, custom  
logo or custom messages

### ID Printing

Add identification to your printed  
documents (date and time,  
short custom message or  
PC username)

### Booklet Printing

Print documents in A5 booklet  
format using automatic or  
manual 2-sided print

### Print Profiles

Store your favourite driver  
settings as profiles to easily  
recall them

### Manual 2-Sided Print

Manual 2-sided printing  
(recommended for media not  
supported by automatic 2-sided  
print)

### Reverse Print

Rotate the content of a printed  
document by 180°

### Carbon Copy

Prints additional copies of the  
same document to paper taken  
from additional paper trays

### Print Complete Notice

A printing notification can be set  
to go to your computer

### Match Media

Assign an ID to a specific tray to  
make the selection of different  
media types from a specific tray  
easier

### Skip Tray

Configures your paper tray  
selection to avoid specific trays/  
media for regular printing

### Job Separation

Insert a different coloured piece  
of paper between different print  
jobs to separate them for easy  
identification

### Secure Print

Protect print jobs with a 4 digit  
release code required at the  
device in order for them to  
be printed

## Printer Driver

### Windows

Windows 11  
(32 and 64 bit editions)  
and more

### macOS

Printing via macOS requires the use of AirPrint. Mac drivers are not provided.

### Linux

CUPS, LPD/LPRng  
(i686 and x86\_64)

### ChromeOS

Supports native  
ChromeOS printing

### PCL Driver

Generic PCL XL driver

### PostScript Universal Printer Driver

Driver for Windows that enables you to print to any network or locally connected Brother printer

Visit [support.brother.com](http://support.brother.com) for the full list of supported OS and to download the latest drivers and software.

## Paper Handling<sup>11</sup>

### Paper Input Standard Tray

520 Sheets

### Multi Purpose Tray

100 Sheets

### Paper Output

150 Sheets A4

### Envelope Printing

Yes from multi purpose tray

### Media Sizes Standard Tray

A4, Letter, B5(JIS), A5, A5(Long Edge), A6, Executive, Legal, Mexico Legal, India Legal, A4 short (270mm), Folio, 16K

### Multi Purpose Tray

Width 69.8 to 215.9 mm,  
Length 127 to 355.6 mm  
Envelope: COM-10, DL, C5,  
Monarch

### Auto 2-Sided

A4

### Media Type and Weights Standard Tray

Plain Paper, Letterhead, Coloured Paper, Thin Paper, Recycled Paper, Thick Paper, 60-163gsm

### Multi Purpose Tray

Plain Paper, Letterhead, Coloured Paper, Thin Paper, Thick Paper, Thicker Paper, Recycled Paper, Bond, Label, Envelope, Env. Thin, Env.Thick, 60-230gsm

### Auto 2-Sided

Plain Paper, Letterhead, Coloured Paper, Thin Paper, Recycled Paper, 64-105gsm

## Mobile and Web Connectivity

*Scanning functionality is not available on single function printers. Please check your model for compatibility.*

### Brother Mobile Connect<sup>17</sup> (Android)

Print from, scan to, preview copies and check the machine status from an Android device

### Brother Mobile Connect<sup>17</sup> (iPad / iPhone)

Print from, scan to, preview copies and check the machine status from an iPad/iPhone

### Apple AirPrint<sup>17</sup>

Print from and scan to most common file types from any AirPrint enabled application

### Brother Print Service Plugin<sup>17</sup>

Print from an Android devices without a dedicated App.

### Mopria™<sup>17</sup>

Print most common file types from Mopria™ supported Android devices

### Web Connect<sup>18</sup>

Print from and scan to without using a PC on Box, Dropbox, Evernote, OneDrive, Google Drive™ OneNote

## Fleet Management Tools

### Unattended Installer<sup>16</sup>

Ability to centrally deploy and customise our drivers and software

### MSI Installer<sup>16</sup>

Modular installers that can be distributed through On-premise Active Directory

### BRAdmin<sup>16,17</sup>

LAN/WAN management software

### Embedded Web Server

Web based print management software embedded onto the device

### Driver Deployment Wizard<sup>16,17</sup>

Easily create print drivers for hassle free deployment over your network

### Mass Deployment Tool<sup>16</sup>

Provides a configuration interface to help manage and deploy device settings

### Status Monitor<sup>16</sup>

Monitor the status of your machine from your computer



## Software

Scanning functionality is not available on single function printers. Please check your model for compatibility.

### Brother iPrint&Scan Desktop<sup>15,17</sup>

Print from, scan to, preview copies and check the machine status from Windows or macOS PC

### Utilities

Provides setup guides, manual, FAQ, troubleshooting and contact to Brother customer service

### Easy Setup

Simple access to drivers and software for the installation of your Brother machine from [support.brother.com](http://support.brother.com)

## Connectivity

### Wired Network

Gigabit Ethernet (10Base-T/100Base-TX/1000Base-T)

### Wireless Network

2.4GHz: IEEE 802.11 b/g/n (Infrastructure Mode)  
IEEE 802.11 g/n (Wi-Fi Direct)

### Wi-Fi Direct®

Print wirelessly without having to go through a wireless access point (both automatic and manual methods supported)

### Wireless Setup Support

Wi-Fi Protected Setup (WPS)

### Wireless Applications

Vertical Pairing

### Mobile

Print from your mobile device with Brother Mobile Connect, Airprint or Mopria

### Local Interface

Hi-Speed USB 2.0

## Security Features

### Wired Network Security

SMTP-AUTH, SSL/TLS (IPPS, HTTPS, SMTP), SNMP v3 802.1x (EAP-MD5, EAP-FAST, PEAP, EAP-TLS, EAP-TTLS), Kerberos, IPsec

### Wireless Network Security

WEP 64/128 bit, WPA-PSK (TKIP/AES), WPA2-PSK (TKIP/AES), WPA3-SAE (AES)  
\*Wi-Fi Direct supports WPA2-PSK (AES) only.  
SMTP-AUTH, SSL/TLS (IPPS, HTTPS, SMTP), SNMP v3, 802.1x (EAP-FAST, PEAP, EAP-TLS, EAP-TTLS), Kerberos, IPsec

### IPv4

ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBIOS name resolution, DNS Resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, SMTP Client, IPP/PPS, FTP Client and Server, CIFS Client, TELNET Server, SNMPv1/v2c/v3, HTTP/HTTPS server, TFTP client and server, ICMP, Web Services (Print/Scan), SNTP Client, Syslog

### Secure Print

Protect print jobs with a 4 digit release code required at the device in order for them to be printed

### E-mail Notifications

Automatically have the device send e-mail alerts when it requires attention, such as when the toner is low or needs replacing

### E-mail Reports

Receive usage reports on a regular basis via e-mail

### Automatic Intrusion Detection

All Brother Print devices are secure by design. Devices automatically recognise security attacks and take preventative measures, including rebooting where necessary, to ensure the device remains secure

### Firmware Updates

In addition to allowing automatic update alerts to install the latest version the printer can be set to not receive older firmware versions to avoid downgrade by an unauthorised user

### Secure Function Lock 3.0

Use a 4 digit pin or a password to identify and authenticate an individual or groups of users over a network. Allows access control for up to 100 users

### Digitally-signed Firmware

The firmware for Brother print devices is digitally signed and secure

### Syslog

Allows IT Admin to access a single application (SIEM tool) to get device status updates for audit purposes over Syslog

### Port-based Network Access Control

(IEEE 802.1x)  
Brother devices are in full compliance with this standard, to allow connection to an 802.1x EAP (Extensible Authentication Protocol) protected network

### Restrict network protocols

The Protocol Control feature allows an administrator to restrict communication protocols (e.g. FTP, Telnet) as required

## Security Features (continued)

### IPv6

NDP, RA, DNS resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, IPP/IPPS, SMTP Client, FTP Client and Server, CIFS Client, TELNET Server, SNMPv1/v2c/v3, HTTP/HTTPS server, TFTP client and server, ICMPv6, SNTP Client, Web Services (Print/Scan), Syslog

### IP Filter

Restrict which network users can or cannot access the device over the network (IPv4 only)

### Cloud Secure Print

Enables password protected driverless print job release

### Setting Lock

Secures access to the devices control panel by locking it

### Certificate Management

Use the default standard self-signed, create a custom self-signed certificate, certificate signing request (CSR), or external public certificate and private key for protected network communication

### Store Print Log

Allows audit of a print log file saved to CIFS server. Record ID, type, name, user, date, time, page count for every print job

## Supplies and Consumables

### Inbox Toner<sup>7</sup>

1 x 6,000 pages (BK)

### Standard Yield Toner<sup>7</sup>

TN3607 - 3,000 pages

### Super High-Yield Toner<sup>7</sup>

TN3607XXL - 11,000 pages

### Max Capacity Yield Toner<sup>7</sup>

TN3617XL - 25,000 pages

### Drum Unit

DR3607 Approx 75,000 pages at 3 pages per job

## Optional Accessories

### Paper Trays

520 sheet tray LT-6505  
4 x 520 sheet tower tray TT-4000

Maximum combinations  
2 x LT-6505

## Solutions and Upgrades<sup>19</sup>

### Brother Pro Upgrades\*

Order Supplies, Remote Panel, Request Help, SecurePrint+, Advance Secure Print and Barcode Print+

*\*Brother Pro Upgrades are optional and will require additional costs.*

## Warranty

### 5-Year On-Site Warranty

When you purchase a Brother printer and our genuine inks or toners, we'll support you every step of the way with our FREE 5-year warranty commitment. YOU DO NOT NEED TO REGISTER YOUR PRODUCT, our warranty is automatic when you purchase your Brother printer. To keep your Brother machine running in optimal condition we recommend using only Brother Genuine Consumables, this will ensure you automatically enjoy our exclusive 5-year warranty.



## Dimensions and Weights

**With Carton (WxDxH)**  
485 x 450 x 402mm - 14.90kg

**Without Carton (WxDxH)**  
373 x 388 x 289mm - 12.70kg

## Duty Cycle

**Recommended Monthly**  
Up to 8,000 pages

## Operating Requirement

**Power Requirement**  
220-240V  
AC 50/60Hz

## Operating Environment

Humidity 20 - 80 %  
10°C - 32.5°C  
50°F - 90.5°F

## Storage Environment

Humidity 35 - 85 %  
0°C - 40°C  
32°F - 104°F

## Environment

**Power Consumption<sup>13,23</sup>**  
Printing: 710W  
Printing in quiet mode: 430W  
Ready: 31W  
Sleep: 5.5W  
Deep Sleep: 0.5W  
Power Off: 0.05W

**TEC Value**  
0.59 kWh/week

## Sound Power<sup>12</sup>

Printing: 7.07B(A)  
Ready: 4.90B(A)  
Quiet Mode: 6.54B(A)  
Deep Sleep: Inaudible

## Sound Pressure<sup>12</sup>

PC Printing (Mono):  
Approx. 54.0dB(A)  
Ready: 35.0db(A)  
Quiet Mode: 50.0db(A)

## Toner Save

This reduces the toner consumption to get more pages from your consumables

- 7 Approx. declared yield value in accordance with ISO/IEC 19752
- 11 Capacity calculated with 80gsm paper
- 12 Sound pressure and sound power level in accordance with ISO 7779
- 13 Power consumption power off is measured according to IEC 62301 Edition 2.0
- 15 Windows and macOS only
- 16 Windows only
- 17 Optional download
- 18 Requires an Internet connection
- 19 Requires additional activation and subject to additional costs
- 23 Power consumption is measured using ENERGY STAR Ver 3.1 test method network configuration



**brother**  
at your side

**Brother International South Africa**  
96 Sovereign Drive, Route 21 Corporate Park, Irene  
Tel 0861 brother Email info@brother.co.za  
www.brother.co.za <https://support.brother.com/>



**BROTHER**  
**CREATIVECENTRE**



Working with you for a better environment  
[www.brotherearth.com](http://www.brotherearth.com)



All specifications correct at time of publication and are subject to change without notice. Brother and its logo are trademarks of Brother Industries LTD., Japan. All registered trademarks referenced herein are the property of their respective companies.