

COLOUR LASER PRINTER Business Efficiency in Vivid Colour

Print

Wireless colour laser printer with intuitive security functions

Built to be truly flexible, the HL-L8360CDW boasts a range of features that can be customised to deliver productivity seamlessly into your business.



Key Features:

Fast print speeds of up to 31ppm colour and mono

Paper input of up to 300 sheets

Maximum paper input of up to 2,380 sheets

Automatic 2-sided printing

Ultra high-yield replacement toners 9,000 pages each: black, cyan, magenta and yellow

High speed wired (10Base-T/100Base-TX/1000Base-T) and wireless (IEEE 802.11b/g/n) network interfaces

Integrated NFC Reader

Intuitive 6.8cm colour touchscreen

Increase productivity levels

- Productivity is increased significantly thanks to the fast print speeds of up to 31ppm in colour and mono
- Maximise your efficiency with built-in wireless IEEE 802.11b/g/n and ethernet 10Base-T/100Base-TX/1000Base-T
- Easily print from your mobile device, using Brother's iPrint&Scan, Brother print service plugin for Android, Google Cloud Print, Mopria and AirPrint
- Outstanding paper handling options with a standard paper capacity of 300 sheets expandable to 2,380 sheets.

Meeting security challenges

- Modern businesses demand the highest levels of security. With Secure Function Lock 3.0, Active Directory Authentication, Internet Protocol Security (IPsec), 802.1x and Secure Print, you can be confident that your documents are safe and secure with near field communication (NFC) functionality.

Flexible and low running costs

- Designed for flexible printing requirements, the HL-L8360CDW includes 6,500 page black, cyan, magenta and yellow inbox toners. Together with a further cost saving of using ultra high-yield replacement cartridges of 9,000 pages per black, cyan, magenta and yellow toners.



General

| | |
|------------------------------------|---|
| Technology | Electrophotographic Laser Printer |
| Laser Classification | Class 1 Laser Product (IEC60825-1:2007) |
| Processor | 800MHz - Sub:133MHz |
| Print Speed Standard (A4) | Up to 31ppm (pages per minute) colour & mono |
| Print Speed 2-Sided (A4) | Up to 14 sides per minute (7 sheets per minute) colour & mono |
| Resolution | 2,400dpi (2,400 x 600dpi), 600 x 600dpi |
| Quiet Mode | A mode to reduce the printing noise by reducing the print speed to 15ppm |
| Memory | 1GB |
| Local Interface | Hi-Speed USB 2.0 & USB Host |
| Wired Network Interface | Ethernet 10Base-T/100Base-TX/1000Base-T |
| Wireless Network Interface | IEEE 802.11b/g/n |
| Display | 6.8cm Colour Touchscreen |
| FPOT (First Print Out Time) | Less than 15 seconds colour & mono from ready mode |
| Warm-Up Time | Less than 29 seconds from sleep mode |
| Print Languages | PCL6, BR-Script3 (PostScript®3™ Language Emulation), PDF 1.7, XPS 1.0 |
| Embedded Fonts (PCL) | 66 scalable fonts, 12 bitmap fonts, 16 barcodes |
| Embedded Fonts (Postscript) | 66 scalable fonts |
| Embedded Barcodes (PCL) | Code39, Interleaved 2 of 5, FIM (US-PostNet), Post Net (US-PostNet), EAN-8, EAN-13, UPC-A, UPC-E, Codabar, ISBN (EAN), ISBN (UPC-E), Code128 (set A, set B, set C), EAN128 (set A, set B, set C), Code93, GS1Databar, MSI |

Printer Driver

| | |
|--|--|
| Windows® | Windows 10® (32 & 64 bit editions) Windows 8® (32 & 64 bit editions) Windows 7® (32 & 64 bit editions) Windows® Server 2016, 2012, 2012R2 & 2008R2 Windows® Server 2008 (32 & 64 bit editions) |
| Macintosh⁵ | Mac OS 10.10.5, 10.11.x, 10.12.x |
| Linux⁵ | CUPS, LPD/LPRng (x86/x64 environment) |
| PostScript Universal Printer Driver | Driver for Windows® that enables you to print to any network or locally connected Brother laser printer that supports PostScript |
| PCL Driver | Generic PCL XL driver |

USB Host

| | |
|---------------------|---|
| Direct Print | Print directly from a USB flash memory drive. The supported file formats include: PDF version 1.7, JPEG, Exif+JPEG, PRN (created by own printer driver), TIFF (scanned by Brother model), XPS version 1.0 |
|---------------------|---|

NFC / Card Reader Support

| | |
|---|--|
| Integrated NFC Reader | Supports NFC cards for secure authentication and NFC supported mobile devices for direct printing. Supported NFC standards include: MIFARE Standard/Plus/Ultralight/Ultralight C/DESfire (ISO14443 Type A), my-d move (ISO14443 Type A), Tag-it (ISO15693) |
| External NFC Card Reader Support. (3rd party card readers require additional purchase. Other card readers supported if registered via the web interface) | Support for external NFC readers via the front USB port. Supported card reader include RFIDeas pcProx Enroll RDR-6081AKU/ RDR-6281AKU/ RDR-6381AKU/ RDR-6E81AKU/ RDR-6H81AKU, RFIDeas AIR ID Enroll RDR-7081AKU/ RDR-7581AKU/ RDR-7F81AKU, Elatec TWN3 Mifare/Mifare NFC.Multi ISO, Elatec TWN4 Mifare NFC |

Standard Paper Handling

| | |
|---------------------------------|---|
| Paper Input² | Standard Tray – 250 sheets Multi Purpose Tray – 50 sheets |
| Paper Output² | Face Down - 150 sheets Face Up (Straight Paper Path) - 1 sheet |

Optional Paper Handling

| | |
|--------------------------------|---|
| Paper Input² | 500 Sheets (LT-340CL) Maximum of 2 optional trays (LT-340CL) 4 x 520 sheet tower tray (TT-4000 & TC-4000) |
|--------------------------------|---|

Paper Sensors

| | |
|--------------|--|
| Input | Onscreen and optional email alerts notifying you when any of the paper input trays are nearly empty or empty |
|--------------|--|

Media Specification

| | |
|--------------------------------------|---|
| Media Types & Weights | Standard Tray – plain, recycled, coloured and letterhead (between 60 - 105g/m ²) Multi Purpose Tray - plain, recycled, bond, coloured, letterhead and glossy ⁸ paper (between 60 -163g/m ²) 2-sided Print - plain, recycled, coloured, letterhead and glossy ⁸ paper (between 60 - 105g/m ²) |
| Envelope & Label Printing | Yes, from the Multi Purpose Tray: support for 10 envelopes up to 10mm total thickness |
| Media Sizes | Standard Tray - A4, Letter, A5, A5(Long Edge), A6, Executive, Legal, Folio Manual Feed Slot - Width: 76.2mm to 215.9mm x Length: 127mm to 355.6mm 2-sided Print - A4 |

Printer Functions

| | |
|---|---|
| N-up Printing³ | Reduce up to 2, 4, 9, 16 or 25 A4 pages into just one A4 page (Mac, up to 2, 4, 6, 9, or 16) |
| Poster Printing⁴ | Enlarge 1 A4 page into a poster using 4, 9, 16 or 25 A4 pages |
| Watermark Printing⁴ | Watermark your documents with predefined text or with your own user-defined messages |
| ID Printing⁴ | Add identification to your printed documents (date & time, short custom message or PC username) |
| Manual 2-Sided Print⁴ | Manual 2-sided printing (recommended for media not supported by automatic 2-sided print) |
| Automatic 2-Sided Print | Print on both sides of the paper automatically |
| Booklet Printing⁴ | Print documents in A5 booklet format using automatic or manual 2-sided print |
| Print Profiles³ | Store your favourite driver settings as profiles to easily recall them |

Mobile / Web Based Printing

| | |
|---|--|
| iPrint&Scan (Android) | Print directly from a smart phone or tablet running the Android Operating System |
| iPrint&Scan (iPad / iPhone) | Print directly from an iPad / iPhone |
| iPrint&Scan (Windows® Phone) | Print directly from a smart phone running the Windows® Phone Operating System |
| Print&Scan (Windows® 8, 10 & RT) | Print directly from a Windows® 8, 10 or Windows RT Tablet |
| Google Cloud Print | Print most common file types from any Google Cloud Print enabled application |
| Apple AirPrint | Print most common file types from any Apple AirPrint enabled application |
| Mopria | Print most common file types from Mopria supported Android devices |
| Android Print Service Plugin | Print from Android devices without a dedicated App |
| Box⁶ | Print from Box without using a PC |
| Dropbox⁶ | Print from Dropbox without using a PC |
| Google Drive⁶ | Print from Google Drive without using a PC |
| OneDrive⁶ | Print from Microsoft OneDrive without using a PC |

Network and Security

| | |
|---|--|
| Wired Network | Built in Ethernet 10Base-T/100Base-TX/1000Base-T |
| Wireless Network | IEEE 802.11b/g/n (Infrastructure Mode / Adhoc Mode) |
| Wi-Fi Direct™ | Print wirelessly without having to go through a wireless access point (both automatic and manual methods supported) |
| Wireless Setup Support | Wi-Fi Protected Setup (WPS) |
| Wireless Applications | Vertical Pairing |
| Network Protocols | TCP/IP (IPv4 and IPv6) |
| IPv4 | ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBIOS name resolution, DNS Resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, IPP/IPPS, FTP Server, TELNET Server, HTTP/HTTPS server, TFTP client and server, SMTP Client, SNMPv1/v2c/v3, ICMP, Web Services (Print), CIFS client, SNTp client, LDAP |
| IPv6 | NDP, RA, DNS resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, IPP/IPPS, FTP Server, TELNET Server, HTTP/HTTPS server, TFTP client and server, SMTP Client, SNMPv1/v2c/v3, ICMPv6, Web Services (Print), CIFS Client, SNTp Client, LDAP |
| Wired Network Security | SMTP-AUTH, SSL/TLS (IPPS, HTTPS, SMTP), SNMP v3, Kerberos, IPSec, 802.1x (EAP-MD5, EAP-FAST, PEAP, EAP-TLS, EAP-TTLS) |
| Wireless Network Security | WEP 64/128 bit, WPA-PSK (TKIP/AES), WPA2-PSK (TKIP/AES), SMTP-AUTH, SSL/TLS (IPPS, HTTPS, SMTP), SNMP v3, Kerberos, IPSec, 802.1x (LEAP, EAP-FAST, PEAP, EAP-TLS, EAP-TTLS) |
| Print Log To Network⁴ | Records printing activities from each individual user, including network username, name of document printed and number of pages, to a file on a network |
| E-mail Notifications | Automatically have the device send an E-mail to a nominated E-mail address when it requires attention |
| E-mail Reports | Receive usage reports on a regular basis via E-mail |
| IP Filter | Restrict which network users can or cannot access the device over the network (IPv4 only) |
| Secure Function Lock 3.0 | Restrict access to individual or groups of users over a network. Can be used with PC User Login Names for up to 200 users |
| Active Directory Authentication | Retrieve stored print jobs using credentials from Active Directory |
| LDAP Authentication | Retrieve stored print jobs using credentials from an LDAP supported database |
| Setting Lock | Restrict access to the control panel |
| Secure Print³ | Protect print jobs with a 4 digit release code required at the device in order for them to be printed |

Fleet Management Tools

| | |
|--|--|
| Unattended Installer⁴ | Ability to centrally deploy and customise our drivers and software |
| MSI Installer⁴ | Modular installers that can be distributed through Active Directory [®] |
| Embedded Web Server | Web based print management software embedded onto the device |
| BRAAdmin Professional³⁴⁵ | LAN/WAN management software |
| Driver Deployment Wizard⁴ | Easily create print drivers for hassle free deployment over your network |

¹ Approx declared yield value in accordance with ISO/IEC 19798

² Calculated with 80g/m² paper

³ Windows[®] & Mac only

⁴ Windows[®] only

⁵ Optional download

⁶ Must be web connected

⁷ Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements

⁸ Only a single sheet supported in the Multi Purpose Tray

Developers

| | |
|---|---|
| Brother Solution Interface (BSI) | Create powerful cloud and on premise solutions directly integrating the advanced print, scan and security capabilities of Brother scanners, printers and all in ones. For more information visit: www.brother.eu/developers |
|---|---|

Supplies & Accessories

| | |
|--------------------------------|---|
| Inbox Toners | Black Toner – 6,500 pages ¹ Cyan, Magenta & Yellow Toners - 6,500 pages ¹ |
| Ultra High Yield Toners | Black Toner (TN-469BK) 9,000 pages ¹ Cyan Toner (TN-469C) 9,000 pages ¹ Magenta Toner (TN-469M) 9,000 pages ¹ Yellow Toner (TN-469Y) 9,000 pages ¹ |
| Other Supplies | Drum (DR-461CL) Approx. 50,000 pages at 3 pages per job Belt (BU-330CL) Approx. 130,000 pages at 3 pages per job Waste Toner Box (WT-320CL) Approx 50,000 pages |
| LT-340CL | Optional 500 Sheet Lower Paper Tray |
| TT-4000 | Optional 4 x 520 sheets Tower Tray (TC-4000 also needed) |
| TC-4000 | Needed to connect to the TT-4000 |
| Carton Contents | Toner Cartridges, Drum, Belt, Waste Toner Box, Power Supply Cord, USB Cable, Driver Software For Windows [®] , Quick Set-Up Guide |

The frequency of replacement consumables will vary depending on the complexity of the prints, the percentage of coverage, paper size, page per job, and the type of media. For example glossy coated paper will result in a shortened life of such supplies.

Environment

| | |
|-----------------------------|--|
| Power Consumption | Printing - 580W, ready - 70W, sleep - 10.0W, deep sleep - 1.5W, power down - 0.03W |
| Sound Pressure Level | Printing - 49dbA, quiet mode printing - 44dbA, ready - inaudible |
| Sound Power Level | Printing - 6.56BA, quiet mode printing - 6.0, ready - inaudible |
| Power Saving | This enables the printer to consume less energy when not in use |
| Toner Saving | This reduces the toner usage and helps to reduce the total cost of printer ownership |

Dimensions & Weight

| | |
|-------------------------------|--------------------------|
| With Carton (WxDxH) | 617 x 558 x 521mm 25.9kg |
| Without Carton (WxDxH) | 441 x 486 x 313mm 21.9kg |

Duty Cycles

| | |
|------------------------------------|---|
| Recommended Monthly | Up to 4,000 pages monthly print volume |
| Maximum Monthly⁷ | Up to 60,000 pages monthly print volume |



Brother strongly recommends the use of genuine Brother consumable products only. Benefits include better quality print, greater yields per consumable, protection of your machine from damages and achievement of optimum performance. As a precaution, please note that your machine warranty may not cover any damages arising from the use of non-genuine consumables.



One-stop centre for free downloadable templates

Microsoft, Windows, the Windows logo and/or other Microsoft products referenced herein are either registered trademarks of Microsoft Corporation in the U.S. and/or other countries. Brother and its logo are trademarks of Brother Industries Ltd., Japan. All specifications are subject to change without notice. All registered trademarks referenced herein are the property of their respective companies. Brother International Corporation, Japan.

brother
at your side

Brother International South Africa

96 Sovereign Drive, Route 21 Corporate Park, Irene
Tel: 0861 BROTHER Fax: +27 (0) 12 - 345 3886

www.brother.co.za <http://solutions.brother.com>



Working with you for a better environment
www.brotherearth.com